

Features

- A handy, versatile and tiltable worklight
- Two high-performance LEDs emit up to 85 Lumens in brightness
- Over 120 degree adjustable angles and easy one-handed operation
- Built-in rechargeable Li-ion battery provides a maximum runtime up to 22 hours
- Integrated intelligent Li-ion battery charging circuit (via micro-USB charging port)
- Dual switch design offers access to all functions via one-handed operation
- Three brightness levels to select from
- Direct access to red light/red flicker mode
- An screw fastened clip for multiple purposes
- Constructed from durable Polycarbonate materials
- Extremely lightweight, compact and portable
- Impact resistant to 1 meter

Dimensions

Size: 2.91"×0.94"×0.62"(74mm×24mm×15.8mm)

Weight: 25g (with battery and clip)

Accessories

Key ring

Output & Runtime

FL1 STANDARD	HIGH	MID	LOW	BLINKING	RED	RED BLINKING
	85 LUMENS	30 LUMENS	2 LUMENS	85 LUMENS	0.25 LUMENS	0.25 LUMENS
	45min	2h 15min	22h	—	13h	14h
	26m	13m	3.7m	—	—	—
	170cd	45cd	3.5cd	—	—	—
	1m (Impact Resistant)					
	IP65 (Dust & Water Resistant)					

NOTICE:

Stated data has been measured in accordance with the international flashlight testing standards ANSI/NEMA FL1 using an integrated and fully charged 3.7V 220mAh rechargeable Li-ion battery under laboratory conditions. End-user results may vary due to individual usage habits and environmental conditions.

Operating Instructions

1. The upper switch controls the white LEDs, and the lower switch controls the red LEDs. Press the upper switch repeatedly within 3 second intervals to switch from High-mid-low-blinking-off, pressing the lower switch repeatedly in the same manner will switch the outputs from constant red-blinking red-off.

Note: There is another red light located between the two main red LEDs. It is lit when a USB cord is plugged in to indicate the battery is taking a charge.

2. To turn the Thumb red light off, either press the lower switch within three second after entering the red blinking mode, or cease any operation in constant red mode for three seconds, and press the lower switch.
3. To turn the Thumb off, either press the upper switch in the blinking mode, or cease any operation in any mode for three seconds, then press the upper switch.


Lockout/Unlock

With the Thumb turned off, press both switches simultaneously to lockout the Thumb. The red power indicator will blink once to indicate the lockout status. In the lockout status, all functions will be rendered inoperational. To unlock, press both switches simultaneously again.

Charging

Remove the port cover to expose the USB charging port. Connect the charger port to an external power source (adapter, computer or other device) via a USB cord.

The power indicator will stay on to indicate charging in progress, it will turn green to indicate charging completed. Fully charges the battery take approximately 3 hours.



Note: Recharged the Thumb when output appears to be dim or unresponsive.

Warranty Service


All NITECORE products are warranted for quality. Any defective / malfunctioning NITECORE Tumb can be repaired free of charge for a period of 24 months from the date of purchase. Beyond 24 months, a limited warranty applies, covering the cost of labor and maintenance, but not the cost of accessories or replacement parts.

The warranty is nullified in all of the following situations:

1. The product(s) is/are broken down, reconstructed and/or modified by unauthorized parties.
2. The product(s) is/are damaged through improper use.

For the latest information on NITECORE products and services, please contact a local NITECORE.

※All images, text and statements specified herein this user manual are for reference purpose only. Should any discrepancy occurs between this manual and information specified on www.nitecore.com, information on our official website shall prevail. SYSMAX Innovations Co., Ltd. reserves the rights to interpret and amend the content of this document at any time without prior notice.



SYSMAX Innovations Co., Ltd.

TEL: +86-20-83862000

FAX: +86-20-83882723

E-mail: info@nitecore.com

Web: www.nitecore.com

Address: Rm 2601-06, Central Tower, No.5 Xiancun Road, Tianhe District, Guangzhou, 510623, Guangdong, China



Made in China